

Модуль безопасности CS AM-01

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +(727)345-47-04

Беларусь +(375)257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: poz@nt-rt.ru || сайт: <https://pizzato.nt-rt.ru/>



Safety modules for motor standstill monitoring

Main features

- For safety applications up to SIL CL 2/PL d
- Select from 10 different residual voltages on motor standstill
- Galvanic separation between control circuit and measurement circuit
- 45 mm housing
- 2 NO safety contacts
- 1 NC auxiliary contact
- 2 semiconductor outputs:
 - 1 signalling output for failure state
 - 1 signalling output for switching state of safety relays
- Possibility to connect single-phase or three-phase motors to measuring circuits
- Supply voltages: 24 ... 230 Vac/dc

Utilization categories

Alternating current: AC15 (50...60 Hz)
 U_e (V) 230
 I_e (A) 3
 Direct current: DC13 (6 oper. cycles/min.)
 U_e (V) 24
 I_e (A) 4

Quality marks:



EC type examination certificate: IMQ CS 487 DM
 UL approval: E131787
 CCC approval: 2021000305000107
 EAC approval: RU C-IT.YT03.B.00035/19

Compliance with the requirements of:

Machinery Directive 2006/42/EC,
 EMC Directive 2014/30/EC,
 RoHS Directive 2011/65/EU.

Technical data

Housing

Polyamide housing PA 66, self-extinguishing V0 acc. to UL 94
 Protection degree acc. to EN 60529: IP40 (housing), IP20 (terminal strip)
 Dimensions: see page 415, design C

General data

SIL level (SIL CL) up to: SIL CL 2 acc. to EN 62061
 Performance Level (PL) up to: PL d acc. to EN ISO 13849-1
 Safety category up to: cat. 3 acc. to EN ISO 13849-1
 Safety parameters: see page 481
 Ambient temperature: -25°C...+55°C
 Mechanical endurance: >10 million operating cycles
 Electrical endurance: >100,000 operating cycles
 Pollution degree: external 3, internal 2
 Rated impulse withstand voltage (U_{imp}): 4 kV
 Rated insulation voltage (U_i): 250 V
 Overvoltage category: II

Supply

Rated supply voltage (U_n): 24 ... 230 Vac/dc; 50...60 Hz
 Max. DC residual ripple in DC: 10%
 Supply voltage tolerance: ±15% of U_n
 Power consumption AC: < 6 VA
 Power consumption DC: < 2 W

Input circuit

Voltage between terminals L1-L2-L3: 0 ... 690 V
 Frequency: 0 ... 3 kHz
 Input impedance: >1 MΩ
 Started motor threshold voltage: from 20 mV to 500 mV adjustable in 10 increments
 Stopped motor threshold voltage: half the motor threshold voltage with motor in operation
 Maximum input impedance Y1-Y2: < 20 Ω
 Current in STARTY1-Y2 circuit: 70 mA (typical)
 RESET input voltage: 24 Vdc ± 20%
 RESET input current: 10 mA (typical)

Control circuit

Response time t_A: < 3 s
 Release time t_R: < 200 ms
 Release time in absence of power supply t_R: < 3 s
 Simultaneity time t_{c1}, t_{c2}: 3 s
 Test: Self-test upon activation of the supply voltage and after activation of the RESET input.
 Test duration: 2.5 s (During the test, the voltage in the measurement circuits must be less than the threshold voltage of the motor while at a standstill)

In compliance with standards:

EN 60204-1, EN ISO 14118, EN ISO 12100, EN 60529, EN 61000-6-2, EN 61000-6-3, EN 61326-1, EN 60664-1, EN 60947-1, EN IEC 63000, EN ISO 13849-1, EN ISO 13849-2, EN 62061, UL 508, CSA C22.2 No. 14, GB/T14048.5

Output circuit

Output contacts: 2 NO safety contacts, 1 NC auxiliary contact
 Contact type: forcibly guided
 Material of the contacts: gold-plated silver alloy
 Maximum switching voltage: 230/240 Vac; 300 Vdc
 Max. current per contact: 6 A
 Conventional free air thermal current I_{th}: 6 A
 Max. total current Σ I_{th}²: 36 A²
 Minimum current: 10 mA
 Contact resistance: ≤ 100 mΩ
 External protection fuse: 4 A
 Semiconductor outputs: PNP outputs galvanically separated, overvoltage and short-circuit protected
 Switching voltage: 24 Vdc
 Switching current: 50 mA
 External supply voltage: 24 Vdc ±20%

The number and the load capacity of output contacts can be increased by using expansion modules or contactors. See pages 355-364.

Code structure

article	options
CS AM-01VE01-TC00UR1	
Connection type V Screw terminals M Connector with screw terminals X Connector with spring terminals	Threshold voltage for motor at standstill 20-500 mV (standard) UR1 45-750 mV
	Simultaneity time (t_c) 3s (standard) TC00 infinite at standstill (t _c) TA00 infinite on startup and standstill(t _c) TD0 infinite on standstill and minimum activation time (t _A)

Features approved by UL

Rated supply voltage (U_n): 24 ... 230 Vac/dc; 50 ... 60 Hz
 Power consumption AC: < 9 VA
 Power consumption DC: < 2 W
 Relay output:
 Electrical ratings: 230/240 Vac
 6 A general use
 C300 pilot duty
 Semiconductor output: 24 Vdc, 50 mA
 Motor input: up to 600 V

Notes:
 - For use in pollution degree 2 environment
 - Use 60 or 75°C copper (Cu) conductor and wire size No. 30-12 AWG, stranded or solid.
 - The terminal tightening torque of 5-7 lb in.

- Pour une utilisation dans un environnement de degré de pollution 2.
 - Utiliser des conducteurs en cuivre (Cu) 60 ou 75°C rigides ou flexibles de section 30-12 AWG.
 - Couple de serrage des bornes de 5-7 Lb In.

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +(727)345-47-04

Беларусь +(375)257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: poz@nt-rt.ru || сайт: <https://pizzato.nt-rt.ru/>