

Выключатели с деталями из нержавеющей стали FK, FR, FX

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +(727)345-47-04

Беларусь +(375)257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: poz@nt-rt.ru || сайт: <https://pizzato.nt-rt.ru/>

Description

Pizzato Elettrica offers a wide range of products suitable for places where chemical and corrosive agents are used and for aseptic places where particular attention must be paid to cleanliness and hygiene.

The technopolymer housings and external metal parts in stainless steel allow these devices to be used for a variety of applications, ranging from the food and pharmaceutical sectors to the chemical and marine sectors.

Main features:

- Technopolymer housings
- External metallic parts exclusively in stainless steel
- Protection degree IP67 (FW, FP series switches)
- Protection degree IP67 and IP69K (FR, FX, FK series sensors)
- Protection degree IP67 and IP69K (SR, ST, HX series sensors)

Resistance against corrosion

Substance	Stainless steel	Technopolymer
Acetylene	■	■
Vinegar	■	■
Acetone	■	■
Acetic acid	■	□
Boric acid	■	■
Citric acid	■	■
Hydrochloric acid 100%	□	□
Chromic acid 5%	■	□
Hydrofluoric acid 100%	■	□
Formic acid	■	□
Phosphoric acid (<40%)	□	■
Lactic acid	■	■
Nitric acid (concentrated)	■	□
Oleic acid	■	■
Sulphuric acid (<10%)	■	□
Sulphuric acid (10-75%)	□	□
Sulphuric acid (75-100%)	□	□
Stearic acid	■	■
Tartaric acid	□	■
White water	■	■
Sea water	□	■
Distilled water	■	■
White spirit	■	■
Ethyl alcohol	■	■
Methyl alcohol	■	■
Liquid ammonia	■	■
Ammonium acetate	■	■
Ammonium carbonate	■	■
Ammonium sulfate	■	■
Leaded petrol	■	■
Unleaded petrol	■	■
Benzol	■	□
Beer	■	■
Butane	■	■
Butanol	■	■
Quicklime	■	■
Calcium chloride	■	■
Calcium hydroxide	■	■
Chloroform	■	■
Aluminium chloride	■	■
Ferrous chloride	□	□
Chrome plating	□	□
Diesel	■	■
Ether	■	■
Formaldehyde 100%	■	□
Furfural	■	■
Gelatine	■	■
Glycerine	■	■
Glucose	■	■
Shellac (orange)	■	■
Hydrogen (gas)	■	■
Iodine	□	■
Milk	■	■
Magnesium chloride	□	■
Magnesium hydroxide	■	■
Magnesium sulphate (Epsom salt)	■	■
Mayonnaise	■	■





Substance	Stainless steel	Technopolymer
Whisky malt	■	■
Molasses	■	■
Nickel chloride	□	□
Aluminium nitrate	■	■
Combustible oils	■	■
Tanning oil	■	-
Linseed oil	■	■
Hydraulic oil (synthetic)	■	■
Mineral Oil	■	■
Motor Oil	■	■
Transformer oil	■	■
Paraffin	■	■
Potassium chloride	■	■
Potassium hydroxide (caustic potash)	■	□
Potassium sulphate	■	■
Propane (liquid)	■	■
Copper sulphate >5%	■	□
Liquid soaps	■	■
Chocolate syrup	■	■
Milk whey	■	-
Sodium bicarbonate	■	■
Sodium bisulphate	□	■
Sodium carbonate	■	■
Sodium chloride	■	■
Sodium hydroxide (80%)	■	□
Sodium hypochlorite (100%)	□	□
Sodium nitrate	■	■
Sodium sulphate	■	■
Sodium sulphide	□	■
Aluminium sulphate	■	■
Ferrous sulphate	■	■
Calcium hydroxide	□	■
Potassium hydroxide	■	■
Sodium hydroxide	-	■
Tanning solutions	■	■
Photographic solutions	-	■
Fruit juice	■	■
Vegetable juice	■	■
Toluene	■	□
Transparent (paint)	■	-
Trichloroethylene	■	■
Whisky and wine	■	■
Zinc plate	□	□
Zinc chloride	■	■
Zinc sulphate	-	■
Sulphur chloride	■	■
Sugar (liquid)	■	■
Sugar beet	■	■

Resistance against corrosion

- No corrosion
- Possible corrosion
- Corrosion
- Data not available







Contact type

R = snap action
L = slow action

Contact block

2	R	FR 201-XM2	2x(1NO-1NC)	FR 202-XM2	2x(1NO-1NC)	FR 205-XM2	2x(1NO-1NC)	FR 207-XM2	2x(1NO-1NC)
5	R	FR 501-XM2	1NO+1NC	FR 502-XM2	1NO+1NC	FR 505-XM2	1NO+1NC	FR 507-XM2	1NO+1NC
6	L	FR 601-XM2	1NO+1NC	FR 602-XM2	1NO+1NC	FR 605-XM2	1NO+1NC	FR 607-XM2	1NO+1NC
9	L	FR 901-XM2	2NC	FR 902-XM2	2NC	FR 905-XM2	2NC	FR 907-XM2	2NC
20	L	FR 2001-XM2	1NO+2NC	FR 2002-XM2	1NO+2NC	FR 2005-XM2	1NO+2NC	FR 2007-XM2	1NO+2NC
Max. speed		page 231 - type 4		page 231 - type 3		page 231 - type 3		page 231 - type 3	
Actuating force		8 N (25 N $\rightarrow$)		6 N (25 N $\rightarrow$)		6 N (25 N $\rightarrow$)		4 N (25 N $\rightarrow$)	
Travel diagrams		page 232 - group 1		page 232 - group 2		page 232 - group 2		page 232 - group 3	





Contact type

R = snap action
L = slow action

Contact block

2	R	FR 215-XM2	2x(1NO-1NC)	/	FR 220-XM2	2x(1NO-1NC)	FR 230-XM2V38	2x(1NO-1NC)	
5	R	FR 515-XM2	➡ 1NO+1NC	FR 5A1-XM2	➡ 1NO+1NC	FR 520-XM2	1NO+1NC	FR 530-XM2V38	➡ 1NO+1NC
6	L	FR 615-XM2	➡ 1NO+1NC	FR 6A1-XM2	➡ 1NO+1NC	/		FR 630-XM2V38	➡ 1NO+1NC
9	L	FR 915-XM2	➡ 2NC	FR 9A1-XM2	➡ 2NC	/		FR 930-XM2V38	➡ 2NC
20	L	FR 2015-XM2	➡ 1NO+2NC	FR 20A1-XM2	➡ 1NO+2NC	FR 2020-XM2	1NO+2NC	FR 2030-XM2V38	➡ 1NO+2NC
Max. speed		page 231 - type 2		page 231 - type 4		1 m/s		page 231 - type 1	
Actuating force		8 N (25 N ➡)		6 N (25 N ➡)		0.07 Nm		0.06 Nm (0.25 Nm ➡)	
Travel diagrams		page 232 - group 1		page 232 - group 1		page 232 - group 4		page 232 - group 5	

Contact type

R = snap action
L = slow action

Contact block

2	R	FR 231-XM2V38	2x(1NO-1NC)	FR 251-XM2V38	2x(1NO-1NC)	FR 254-XM2V38	2x(1NO-1NC)	FR 256-XM2V38	2x(1NO-1NC)
5	R	FR 531-XM2V38	1NO+1NC	FR 551-XM2V38	1NO+1NC	FR 554-XM2V38	1NO+1NC	FR 556-XM2V38	1NO+1NC
6	L	FR 631-XM2V38	1NO+1NC	FR 651-XM2V38	1NO+1NC	FR 654-XM2V38	1NO+1NC	FR 656-XM2V38	1NO+1NC
9	L	FR 931-XM2V38	2NC	FR 951-XM2V38	2NC	FR 954-XM2V38	2NC	FR 956-XM2V38	2NC
20	L	FR 2031-XM2V38	1NO+2NC	FR 2051-XM2V38	1NO+2NC	FR 2054-XM2V38	1NO+2NC	FR 2056-XM2V38	1NO+2NC
Max. speed		page 231 - type 1		page 231 - type 1		page 231 - type 1		page 231 - type 1	
Actuating force		0.06 Nm (0.25 Nm $\rightarrow$)		0.06 Nm (0.25 Nm $\rightarrow$)		0.06 Nm (0.25 Nm $\rightarrow$)		0.06 Nm (0.25 Nm $\rightarrow$)	
Travel diagrams		page 232 - group 5		page 232 - group 5		page 232 - group 5		page 232 - group 5	

Switches with external parts in **stainless steel**

Contact type R = snap action L = slow action									
Contact block									
2	R	FX 201-XM2	2x(1NO-1NC)	FX 202-XM2	2x(1NO-1NC)	FX 205-XM2	2x(1NO-1NC)	FX 207-XM2	2x(1NO-1NC)
5	R	FX 501-XM2	➔ 1NO+1NC	FX 502-XM2	➔ 1NO+1NC	FX 505-XM2	➔ 1NO+1NC	FX 507-XM2	➔ 1NO+1NC
6	L	FX 601-XM2	➔ 1NO+1NC	FX 602-XM2	➔ 1NO+1NC	FX 605-XM2	➔ 1NO+1NC	FX 607-XM2	➔ 1NO+1NC
9	L	FX 901-XM2	➔ 2NC	FX 902-XM2	➔ 2NC	FX 905-XM2	➔ 2NC	FX 907-XM2	➔ 2NC
20	L	FX 2001-XM2	➔ 1NO+2NC	FX 2002-XM2	➔ 1NO+2NC	FX 2005-XM2	➔ 1NO+2NC	FX 2007-XM2	➔ 1NO+2NC
Max. speed		page 231 - type 4		page 231 - type 3		page 231 - type 3		page 231 - type 3	
Actuating force		8 N (25 N ➔)		6 N (25 N ➔)		6 N (25 N ➔)		4 N (25 N ➔)	
Travel diagrams		page 232 - group 1		page 232 - group 2		page 232 - group 2		page 232 - group 3	





Contact type R = snap action L = slow action				External gasket 		External gasket 			
Contact block									
2	R	FX 215-XM2	2x(1NO-1NC)	FX 220-XM2	2x(1NO-1NC)	FX 225-XM2	2x(1NO-1NC)	FX 230-XM2V38	2x(1NO-1NC)
5	R	FX 515-XM2	➔ 1NO+1NC	FX 520-XM2	1NO+1NC	FX 525-XM2	1NO+1NC	FX 530-XM2V38	➔ 1NO+1NC
6	L	FX 615-XM2	➔ 1NO+1NC	/	/	/	/	FX 630-XM2V38	➔ 1NO+1NC
9	L	FX 915-XM2	➔ 2NC	/	/	/	/	FX 930-XM2V38	➔ 2NC
20	L	FX 2015-XM2	➔ 1NO+2NC	FX 2020-XM2	1NO+2NC	FX 2025-XM2	1NO+2NC	FX 2030-XM2V38	➔ 1NO+2NC
Max. speed		page 231 - type 2		1 m/s		1 m/s		page 231 - type 1	
Actuating force		8 N (25 N ➔)		0.07 Nm		0.12 Nm		0.06 Nm (0.25 Nm ➔)	
Travel diagrams		page 232 - group 1		page 232 - group 4		page 232 - group 4		page 232 - group 5	

Contact type R = snap action L = slow action									
Contact block									
2	R	FX 231-XM2V38	2x(1NO-1NC)	FX 251-XM2V38	2x(1NO-1NC)	FX 254-XM2V38	2x(1NO-1NC)	FX 256-XM2V38	2x(1NO-1NC)
5	R	FX 531-XM2V38	➔ 1NO+1NC	FX 551-XM2V38	➔ 1NO+1NC	FX 554-XM2V38	➔ 1NO+1NC	FX 556-XM2V38	➔ 1NO+1NC
6	L	FX 631-XM2V38	➔ 1NO+1NC	FX 651-XM2V38	➔ 1NO+1NC	FX 654-XM2V38	➔ 1NO+1NC	FX 656-XM2V38	➔ 1NO+1NC
9	L	FX 931-XM2V38	➔ 2NC	FX 951-XM2V38	➔ 2NC	FX 954-XM2V38	➔ 2NC	FX 956-XM2V38	➔ 2NC
20	L	FX 2031-XM2V38	➔ 1NO+2NC	FX 2051-XM2V38	➔ 1NO+2NC	FX 2054-XM2V38	➔ 1NO+2NC	FX 2056-XM2V38	➔ 1NO+2NC
Max. speed		page 231 - type 1		page 231 - type 1		page 231 - type 1		page 231 - type 1	
Actuating force		0.06 Nm (0.25 Nm ➔)		0.06 Nm (0.25 Nm ➔)		0.06 Nm (0.25 Nm ➔)		0.06 Nm (0.25 Nm ➔)	
Travel diagrams		page 232 - group 5		page 232 - group 5		page 232 - group 5		page 232 - group 5	

All values in the drawings are in mm







Contact type

R = snap action
L = slow action

Contact block

3	R	FK 301-XM2	1NO+1NC
33	L	FK 3301-XM2	1NO+1NC
34	L	FK 3401-XM2	2NC
Max. speed		page 231 - type 4	
Actuating force		8 N (25 N)	
Travel diagrams		page 232 - group 1	
		page 231 - type 3	
		6 N (25 N)	
		page 232 - group 2	
		page 231 - type 3	
		6 N (25 N)	
		page 232 - group 2	
		page 231 - type 3	
		4 N (25 N)	
		page 232 - group 3	





Contact type

R = snap action
L = slow action

Contact block

3	R	FK 315-XM2	1NO+1NC
33	L	FK 3315-XM2	1NO+1NC
34	L	FK 3415-XM2	2NC
Max. speed		page 231 - type 2	
Actuating force		8 N (25 N)	
Travel diagrams		page 232 - group 1	
		1 m/s	
		0.05 Nm	
		page 232 - group 4	
		1 m/s	
		0.1 Nm	
		page 232 - group 4	
		page 231 - type 1	
		0.06 Nm (0.25 Nm)	
		page 232 - group 5	

Contact type





R = snap action
L = slow action

Contact block

3	R	FK 331-XM2V38	1NO+1NC
33	L	FK 3331-XM2V38	1NO+1NC
34	L	FK 3431-XM2V38	2NC
Max. speed		page 231 - type 1	
Actuating force		0.06 Nm (0.25 Nm)	
Travel diagrams		page 232 - group 5	
		page 231 - type 1	
		0.06 Nm (0.25 Nm)	
		page 232 - group 5	
		page 231 - type 1	
		0.06 Nm (0.25 Nm)	
		page 232 - group 5	

Contact type

R = snap action
L = slow action






Contact block

2	R	FP 201-XM2	2x(1NO-1NC)	FP 202-XM2	2x(1NO-1NC)	FP 205-XM2	2x(1NO-1NC)	FP 208-XM2	2x(1NO-1NC)
5	R	FP 501-XM2	1NO+1NC	FP 502-XM2	1NO+1NC	FP 505-XM2	1NO+1NC	FP 508-XM2	1NO+1NC
6	L	FP 601-XM2	1NO+1NC	FP 602-XM2	1NO+1NC	FP 605-XM2	1NO+1NC	FP 608-XM2	1NO+1NC
9	L	FP 901-XM2	2NC	FP 902-XM2	2NC	FP 905-XM2	2NC	FP 908-XM2	2NC
20	L	FP 2001-XM2	1NO+2NC	FP 2002-XM2	1NO+2NC	FP 2005-XM2	1NO+2NC	FP 2008-XM2	1NO+2NC
Max. speed		page 229 - type 4		page 229 - type 3		page 229 - type 3		page 229 - type 4	
Actuating force		8 N (25 N $\rightarrow$)		6 N (25 N $\rightarrow$)		6 N (25 N $\rightarrow$)		8 N (25 N $\rightarrow$)	
Travel diagrams		page 230 - group 1		page 230 - group 2		page 230 - group 2		page 230 - group 1	

Contact type

R = snap action
L = slow action

External gasket






Contact block

2	R	FP 210-XM2	2x(1NO-1NC)	FP 211-XM2	2x(1NO-1NC)	FP 216-XM2	2x(1NO-1NC)
5	R	FP 510-XM2	1NO+1NC	FP 511-XM2	1NO+1NC	FP 516-XM2	1NO+1NC
6	L	FP 610-XM2	1NO+1NC	FP 611-XM2	1NO+1NC	FP 616-XM2	1NO+1NC
9	L	FP 910-XM2	2NC	FP 911-XM2	2NC	FP 916-XM2	2NC
20	L	FP 2010-XM2	1NO+2NC	FP 2011-XM2	1NO+2NC	FP 2016-XM2	1NO+2NC
Max. speed		page 229 - type 4		page 229 - type 4		page 229 - type 2	
Actuating force		11 N (25 N $\rightarrow$)		8 N (25 N $\rightarrow$)		8 N (25 N $\rightarrow$)	
Travel diagrams		page 230 - group 1		page 230 - group 1		page 230 - group 1	

Safety switches for hinges

Contact type

L = slow action



Contact block

9	L	FR 996-XM2	2NC	FX 996-XM2	2NC	/
18	L	FR 1896-XM2	1NO+1NC	FX 1896-XM2	1NO+1NC	/
20	L	FR 2096-XM2	1NO+2NC	FX 2096-XM2	1NO+2NC	/
33	L	/	/	/	/	FK 3396-XM2 1NO+1NC
34	L	/	/	/	/	FK 3496-XM2 2NC
Actuating force		0.15 Nm (0.4 Nm $\rightarrow$)		0.15 Nm (0.4 Nm $\rightarrow$)		0.15 Nm (0.4 Nm $\rightarrow$)
Travel diagrams		page 234 - group 9		page 234 - group 9		page 234 - group 9

⚠ If not expressly indicated in this chapter, for correct installation and utilization of all articles see the instructions given on pages 227 to 242.



Safety switches with separate actuator

Contact type

= slow action

	Without actuator		Without actuator		Without actuator		Without actuator	
Contact block								
6		FR 693-XM2		1NO+1NC	FX 693-XM2		1NO+1NC	/
9		FR 993-XM2		2NC	FX 993-XM2		2NC	/
20		FR 2093-XM2		1NO+2NC	FX 2093-XM2		1NO+2NC	/
33		/		/	/		/	FK 3393-XM2
34		/		/	/		/	FK 3493-XM2
Actuating force	10 N (18 N		10 N (18 N		10 N (18 N		10 N (18 N	
Travel diagrams	page 234 - group 8		page 234 - group 8		page 234 - group 8		page 234 - group 8	

Stainless steel actuators

IMPORTANT: These actuators can be used only with items of the FR, FX, FK and FW series (e.g. FR 693-XM2).
Low level of coding acc. to EN ISO 14119.

Article	Description	Article	Description
VF KEYD	Straight actuator	VF KEYD1	Angled actuator
Article	Description	Article	Description
VF KEYD5	Extended actuator	VF KEYD6	Extended actuator, angled
Article	Description	Article	Description
VF KEYD8	Universal actuator	VF KEYD10	Profiled actuator

SR series magnetic safety sensors



See
General Catalogue Safety 2023-2024

ST series RFID safety sensors



See
General Catalogue Safety 2023-2024

HX series stainless steel safety switches



See
General Catalogue Safety 2023-2024



По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +(727)345-47-04

Беларусь +(375)257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: poz@nt-rt.ru || сайт: <https://pizzato.nt-rt.ru/>